




hether you require the use of a booster pump or pull water directly from a creek or pond, it is imperative that your irrigation system includes a relay that can be counted upon to activate your pump each and every time. The Pump Start Relays have been created to provide that reliability – as well as a lockable NEMA rated enclosure – at an economical price. Available in

a choice of three models to accommodate a variety of power sources and landscape needs, the product is fully compatible with all standard 24VAC controllers. It's also designed with user-friendliness in mind, with flying leads that allow for effortless 24 volt connections plus a wide array of "knockouts" on the cabinet to make wiring easy, whatever your particular mounting considerations.

FEATURES & BENEFITS



NEMA 3R rated locking enclosure Enclosure has a high rating for outdoor use and

is weatherproof, secure, rust-resistant and shock proof

Choice of 3 different models

Internal hardware has been sized accordingly to fit your particular voltage and landscape requirements

24VAC flying leads

Makes connections to controller quick and easy

Compact design

Enclosure measures 7.5" H x 6.5" W x 4.5" D

Completely UL approved

The PSR-22 meets the demanding electrical requirements necessary for UL approval for both relay and cabinet. The PSR-52 and PSR-53 contain UL approved contactors.

ELECTRICAL SPECIFICATIONS							
MODELS	SINGLE HP @ 110	PHASE HP @ 220	3 PHASE HP @ 230	MAX FULL LOAD Amps	MAX RESISTIVE AMPS	COIL VA Inrush	COIL VA Holding
PSR-22	2*	5*	N/A	22	22	65	11
PSR-52	5	7.5	N/A	40	50	65	11
PSR-53	5	7.5	10	40	50	56	6
*Approximate horsenower							

*Approximate horsepower

Hunter Industries Incorporated • The Irrigation Innovators

1940 Diamond Street • San Marcos, California 92069 • TEL: (1) 760-744-5240 • FAX: (1) 760-744-7461 www.HunterIndustries.com

© 2001 Hunter Industries Incorporated P/N 700449 LIT-257.PDF 6/01

PSR

This Pump Start Relay Provides Reliability at an Economical Price

